

# 200W High Power Draw Bar Box 8 Channels Mobile Signal Jammer RF frequencies 315 433 868MHz bomb jammer

## Application Area:

Meeting Halls,infantry,military Security Force,SWAT Team,bomb Squad,anti-terrorism Units,anti-drag Units,anti-riot Force,the EOD Team,checkpoints, Hostage Negotiations,border Control,etc..

Parameter **Shielding Range:** Radius 100-300 meters(-75dBm,depending on the distance of base station in an open filed)

**Transmission Power:** Integrated Equipment $\geq$ 200W,each channel $\geq$ 25W

## Jammed Signal Types:

CDMA/GSM:850~894MHz, or 925~960MHz

DCS:1805~1880MHz, or 1920~1990MHz

3G:2110~2170MHz,

4G:2345~2400 or 2620~2690MHz,

4G1:725~770MHz or 790~826MHz

315MHz,

433MHz,

868MHz



**Other Signal Types:**VHF,UHF,GPSL1-L5,WIFI5.8G,etc

**Output Channel:** 8 output channels

Features \*Large coverage, covering all 2G, 3G and 4G signals.

\*Draw-bar box designed for portability and easy moving;

\*Built-in rechargeable battery can be used for 90~120 minutes after being fully charged;

\*Military standard casing, which is anti-throw, pressure-resistant and durable;

\*AC110-220V/Built-in battery supply (DC24V)/Vehicle power supply (DC24V);

\*Built-in efficient cooling fan and cooling fin ensures the product work stably in a long service life;

# 200W High Power Draw Bar Box 8 Channels Mobile Signal Jammer RF frequencies 315 433 868MHz bomb jammer

## Component Dimensions

Name	L	W	H	Remarks
Host	556	455	266	Protrusions excluded
Antenna	375 Φ29			

## Other Parameters

Total Weight	60kg
Ambient Temperature	-10°C~+50°C
Relative Humidity	≤80%
Power Consumption	≤360W
Power Input	AC100~240V,DC24V
Battery	24V,33AH,Built-in standby battery can used for 90~120 minutes
Antenna Parameters	Omni antennas,gain:4~5dBi
Switch Control	Manually
Equipment Chassis	Metallic Paint

